

User's Manual

PPC-090T



DMP Vortex86 DX2 Processor

Compact Panel PC with 9" Touchscreen

PPC-090T-D2N3N

PPC-090T-D2N4N

PPC-090T-D2N3N-GE

PPC-090T-D2N4N-GE

PPC-090T-D2W4N

PPC-090T-D2W4N-GE

(Revision 1.1A)

REVISION

DATE	VERSION	DESCRIPTION
2014/1/22	Version 1.0A	New Release
2014/3/11	Version 1.1A	Add 4.3 Serial Ports Setting (RS232/422/485)

SAFETY INFORMATION

- Read these Safety instructions carefully.
- Please carry the unit with both hands, handle carefully.
- Make sure the voltage of the power source is correct before connecting the equipment to the power outlet.
- Do not expose your Panel PC to rain or moisture in order to prevent shock and fire hazard.
- Input voltage rated +12 ~ 24 VDC
- Operating temperature between 0~+50°C (+32~+122°F).
- Keep PPC-090T away from humidity.
- When a Compact Flash Card or a SATA Slim is the main operating system storage, please turn off power before inserting or removing. Do not open the cabinet to avoid electrical shock. Refer to your nearest dealer for qualified personnel servicing.
- Never touch un-insulated terminals or wire unless your power adaptor is disconnected.
- Locate your Panel PC as close as possible to the socket outline for easy access and to avoid force caused by entangling of your arms with surrounding cables from the Panel PC.
- USB connectors are not supplied with Limited Power Sources.
- If the equipment is not used for a long time, disconnect it from the power source to avoid damage by transient overvoltage.

WARNING!



DO NOT ATTEMPT TO OPEN OR TO DISASSEMBLE THE CHASSIS (ENCASING) OF THIS PRODUCT. PLEASE CONTACT YOUR DEALER FOR SERVICING FROM QUALIFIED TECHNICIAN.

Content

Ch. 1 General Information	1
1.1 Product Description	2
1.2 Product Specifications	3
1.3 Inspection Standard for TFT-LCD Panel.....	5
1.4 Product Dimensions.....	7
1.5 Panel Mounting Instruction	9
1.6 Ordering Information.....	11
Ch. 2 System Installation	12
2.1 CPU Board Outline	13
2.2 Connector Summary	14
2.3 Connector Pin Assignments.....	15
2.4 External I/O Overview	16
2.5 External I/O Pin Assignment	17
2.6 Watchdog Timer.....	18
Ch. 3 Hardware Installation	19
3.1 Installing the SATA Slim	20
3.2 Installing the Compact Flash.....	21
Ch. 4 Driver Installation	22
4.1 PPC-090T Development Note	24
4.2 BIOS Default Setting.....	25
4.3 Serial Ports Setting (RS232/422/485).....	26
Warranty	29

Ch. 1

General Information

[1.1 Product Description](#)

[1.2 Product Specifications](#)

[1.3 Inspection standard for TFT-LCD Panel](#)

[1.4 Product Dimensions](#)

[1.5 Mounting Instruction](#)

[1.6 Ordering Information](#)

1.1 Product Description

ICOP Technology Inc. is proudly going to release a brand new Panel PC, which offers fanless design, low power consumption, and IP65 front panel. The PPC-090T is powered by DMP's latest Vortex86DX2 SoC, the 3rd generation SoC of Vortex86 family, and dual-channel 1GB DDRII chipset that handles processing more efficiently and provides faster performance. The resistive touch panel with LED backlight TFT LCD increases operation convenience and visibility in outdoor environments. The ultra-compact and thin exterior design is perfect for the present demanding embedded and productive applications.

The new PPC-090T inherited PDX/PMX-series' smooth appearance and ultra-texture aluminum exterior design to make your industrial applications look more stylish. The versatile I/O ports, IP65 front panel, 10/100Mbps Ethernet, GIGA high-speed Ethernet, WiFi,...etc. can fulfill fundamental functions. Our consistent advantages feature stable performance, extended working temperature support, low power consumption and fanless design. The expandable customize I/O ports can be accommodated connectivity requirements to industrial machine platforms and industrial automation equipment's needs.

The PPC-090T supports Windows Embedded CE, Windows Embedded Standard 2009, Windows Embedded Compact 7, and Linux to meet ready-to-market demand and provide competitive advantages for customers.

1.2 Product Specifications

CPU BOARD SPECIFICATIONS

CPU	DM&P Vortex86DX2 933MHz
Cache	L1:16KB I-Cache, 16KB D-Cache / L2: 4-way 256KB Cache
BIOS	AMI BIOS
Memory	512MB / 1GB /2GB DDR2 onboard
Watchdog Timer	Software Programmable from 30.5u to 512 seconds x 2 sets
LAN	Integrated 10/100M Ethernet X1 Giga Ethernet (Optional) X1
Audio	HD Audio-Realtek ALC262 CODEC
Internal Drives	Compact Flash Type I / II Slot, SATA SLIM SD Slot (Optional)
I/O	RS-232/422/485 x 2 USB Ports (Ver2.0) x 3 PS/2 KB Audio-Out RJ-45 Port x 1 GIGA Ethernet Port X 1 (Optional)

MECHANICAL & ENVIRONMENT

Power Requirement	+12 ~ 24VDC
Power Consumption	MAX : +24VDC@ 1A
Operating Temperature	0~+50°C (+32~+122°F) / -20~+60°C (-4~+140°F)

Storage Temperature	-30~+70°C (-22~ +158°F)
Operating Humidity	0% ~ 90% Relative Humidity, Non-Condensing
Dimensions	242x156.5x44mm (9.68"x6.26"x1.76")
Weight	3.0 Kg
Protection	IP65 Front Panel
Certification	CE / FCC / VCCI / Vibration

LCD SPECIFICATIONS

Display Type	9" WSVGA TFT LCD
Backlight Unit	LED
Display Resolution	1024(W) x 600(H)
Brightness (cd/m ²)	300 nits
Contrast Ratio	500 : 1
Display Color	262,144
Pixel Pitch (mm)	190.5 (H) x 189 (V)
Viewing Angle	Vertical 140°, Horizontal 160°
Backlight Lifetime	25,000 hrs

TOUCHSCREEN


Type	Analog Resistive
Resolution	Continuous
Transmittance	80%
Controller	PS/2 interface
Software Driver	Linux / WinCE / Windows XP
Durability	1 million

1.3 Inspection Standard for TFT-LCD Panel


DEFECT TYPE		LIMIT		Not e				
VISUAL DEFECT	INTERNAL	SPOT	$\varphi < 0.15\text{mm}$	Ignore	Note 1			
			$0.15\text{mm} \leq \varphi \leq 0.5\text{mm}$	$N \leq 4$				
			$0.5\text{mm} < \varphi$	$N = 0$				
		FIBER	$0.03\text{mm} < W \leq 0.1\text{mm}, L \leq 5\text{mm}$	$N \leq 3$		Note 1		
			$1.0\text{mm} < W, 1.5\text{mm} < L$	$N = 0$				
			POLARIZER BUBBLE	$\varphi < 0.15\text{mm}$			Ignore	Note 1
	$0.15\text{mm} \leq \varphi \leq 0.5\text{mm}$	$N \leq 2$						
	$0.5\text{mm} < \varphi$	$N = 0$						
	Mura	It' OK if mura is slight visible through 6%ND filter						
	ELECTRICAL DEFECT	BRIGHT DOT	A Grade			B Grade		
C Area			O Area	Total	C Area	O Area	Total	
$N \leq 0$			$N \leq 2$	$N \leq 2$	$N \leq 2$	$N \leq 3$	$N \leq 5$	Note 2
DARK DOT		$N \leq 2$	$N \leq 3$	$N \leq 3$	$N \leq 3$	$N \leq 5$	$N \leq 8$	
TOTAL DOT		$N \leq 4$			$N \leq 5$	$N \leq 6$	$N \leq 8$	Note 2
TWO ADJACENT DOT		$N \leq 0$	$N \leq 1$ pair	$N \leq 1$ pair	$N \leq 1$ pair	$N \leq 1$ pair	$N \leq 1$ pair	Note 4
THREE OR MORE ADJACENT DOT		NOT ALLOWED						
LINE DEFECT	NOT ALLOWED							

- (1) One pixel consists of 3 sub-pixels, including R, G, and B dot. (Sub-pixel = Dot)
- (2) Little bright Dot acceptable under 6% ND-Filter.
- (3) If require G0 grand (Total dot $N \leq 0$), please contact region sales.**


[Note 1] W: Width[mm]; L: Length[mm]; N: Number; φ : Average Diameter.



[**Note 2**] Bright dot is defined through 6% transmission ND Filter as following.




[**Note 3**] Display area



C Area: Center of display area **O Area:** Outer of display area


[**Note 4**] Judge the defect dot and the adjacent dot as following. Allow below (as A, B, C and D status) adjacent defect dots, including bright and dark adjacent dot. And they will be counted 2 defect dots in total quantity.




The defects that are not defined above and considered to be problem shall be reviewed and discussed by both parties.

Defects on the Black Matrix, out of Display area, are not considered as a defect or counted.


1.4 Product Dimensions






1.5 Panel Mounting Instruction

1. Cut a mounting hole in the panel. (Refer to [PPC-090T Dimensions](#) on page 7~8.) (Note 1)
2. Check and remove the twelve M3 screws in a diagonal pattern as image below if necessary.
3. Place PPC-090T face-down on a clean, flat surface.
4. Slide the panel cutout around the back of PPC-090T, until the panel rests directly on the gasket. Make sure the screw holes align with the screw holes on PPC-090T.
5. The screw size is M3*L (L=wall thickness + 6.0mm) (Note 2)
6. Insert all twelve M3 screws into the screw holes. (Note 2)
7. Finger-tighten the M3 screws. Finish tightening the M3 screws in a diagonal pattern using an M3 screw driver (see the image as below); maximum torque 1.18Nm (12 kgf-cm).





Note 1:

It is strongly recommended that a professional machine shop cut the mounting hole in the panel.



Note 2:

The length for all twelve M3 screws will be according to the thickness of mounting panel. For example: The length of standard M3 screws for PPC-090T is 6mm. If the thickness of your mounting panel is 3mm and washer thickness is 1mm, you have to use 10mm M3 screw.

1.6 Ordering Information

PART NUMBER	DESCRIPTION
PPC-090T-D2N3N	9" Panel PC w/512MB Memory / 3USB / AUDIO / LAN / 2COM / DC12~24V
PPC-090T-D2N4N	9" Panel PC w/1GB Memory / 3USB / AUDIO / LAN / 2COM / DC12~24V
PPC-090T-D2N3N-GE	9" Panel PC w/512MB Memory / 3USB / AUDIO / LAN / GigaLAN / 2COM / DC12~24V
PPC-090T-D2N4N-GE	9" Panel PC w/1GB Memory / 3USB / AUDIO / LAN / GigaLAN / 2COM / DC12~24V
PPC-090T-D2W4N	9" Panel PC w/1GB Memory / 3USB / AUDIO / LAN / 2COM / DC12~24V / Wide Temp
PPC-090T-D2W4N-GE	9" Panel PC w/1GB Memory / 3USB / AUDIO / LAN / GigaLAN / 2COM / DC12~24V / Wide Temp

PACKING LIST

PART NUMBER	PACKAGE	
PPC-090T-D2N3N	PPC-090T-D2N3N*1	M4 L8 Screw *4
PPC-090T-D2N4N	PPC-090T-D2N4N*1	M4 L8 Screw *4
PPC-090T-D2N3N-GE	PPC-090T-D2N3N-GE*1	M4 L8 Screw *4
PPC-090T-D2N4N-GE	PPC-090T-D2N4N-GE*1	M4 L8 Screw *4
PPC-090T-D2W4N	PPC-090T-D2W4N*1	M4 L8 Screw *4
PPC-090T-D2W4N-GE	PPC-090T-D2W4N-GE*1	M4 L8 Screw *4

Ch. 2

System Installation

[2.1 CPU Board Outline](#)

[2.2 Connector Summary](#)


[2.3 Connector Pin Assignments](#)

[2.4 External I/O Overview](#)

[2.5 External I/O Pin Assignment](#)

[2.6 Watchdog Timer](#)

2.1 CPU Board Outline



PPC CPU Board

2.2 Connector Summary

No.	Description	Type of Connections	Pin #
J1	Power Terminal Connector	External Power Plug	3-pin
J3	COM (RS232/422/485)	External D-Sub Male Connector	9-pin
J4	USB	External USB Connector	6-pin
J5	USB	External USB Connector	6-pin
J6	PS/2Keyboard	External Mini DIN Socket	6-pin
J7	USB	External USB Connector	6-pin
J8	USB (Wi-Fi Optional)	Internal USB Connector	5-pin
J11	Ethernet	External RJ45 Connector	8-pin
J12	GIGA Ethernet	External RJ45 Connector	8-pin
J14	VGA	2.0mm 10-pin box header	10-pin
J16	SD Card Slot (Optional)	Internal SD Card Socket	
J19	RS-232-422-485	2.0mm 10-pin box header	10-pin
J25	SATA Slim Slot	Internal SATA Slim Socket	
J30	Audio Line-Out	1.25mm Phone Jack	2-pin
CF1	CF Card Socket	CF Type I/II Socket	

2.3 Connector Pin Assignments

J1: Power Terminal Connector

Pin #	Signal Name
1	+12~24V
2	GND
3	FG

J3: COM (RS232/422/485)

Pin #	Signal Name
1	DCD1/422TX-/RS485-
2	RXD1/422TX+ /RS485+
3	TXD1/422RX+
4	DTR1/422RX-
5	GND
6	DSR1
7	RTS1
8	CTS1
9	RI1

J4: USB

Pin #	Signal Name	Pin #	Signal Name
1	VCC	2	USBD2-
3	USBD2+	4	GND
5	GND	6	GND

J5: USB

Pin #	Signal Name	Pin #	Signal Name
1	VCC	2	USBD3-
3	USBD3+	4	GND
5	GND	6	GND

J7: USB

Pin #	Signal Name	Pin #	Signal Name
1	VCC	2	USBD4-
3	USBD4+	4	GND
5	GND	6	GND

J8: USB (Wi-Fi Optional)

Pin #	Signal Name	Pin #	Signal Name
1	VCC	2	USBD1-
3	USBD1+	4	GND
5	GND		

J6: PS/2Keyboard

Pin #	Signal Name	Pin #	Signal Name
1	KBCLK	2	MSCLK
3	GND	4	KBDATA
5	MSDATA	6	VCC
7	GND	8	GND
9	GND		


J14: VGA

Pin #	Signal Name	Pin #	Signal Name
1	R OUT	2	GND
3	G OUT	4	GND
5	B OUT	6	GND
7	HSYNC	8	GND

J19: RS-232-422-485

Pin #	Signal Name	Pin #	Signal Name
1	R OUT	2	GND
3	G OUT	4	GND
5	B OUT	6	GND
7	HSYNC	8	GND
9	VSYNCD	10	GND

2.4 External I/O Overview




NOTE


1. The functions of GIGA LAN, Wireless are optional
2. The serial ports RS232/422/485 are selected by BIOS setting, please refer to [4.3 Serial Ports Setting \(RS232/422/485\)](#)

2.5 External I/O Pin Assignment


Power Switch

	Pin #	Status
		ON
	O	OFF


Power Connector DC-IN 24V

	Pin #	Signal Name
	1	+12~24V
	2	GND
	3	FG


PS/2 Keyboard

	Pin #	Signal Name
	1	KBCLK
	2	PMCLK
	3	GND
	4	KBDAT
	5	PMDAT
	6	SB5V


J3: COM-RS232/422/485 (Change setting by BIOS)

	Pin #	Signal Name
	1	DCD1/422TX-/RS485-
	2	RXD1/422TX+/RS485+
	3	TXD1 / 422RX+
	4	DTR1 / 422RX-
	5	GND
	6	DSR1
	7	RTS1
	8	CTS1
	9	RI1


J4/J5/J7: USB

	Pin #	Signal Name
	1	VCC
	2	USB0-
	3	USB0+
	4	GND
	5	GGND
6	GGND	

RJ45

	Pin #	Signal Name	Pin #	Signal Name
	1	FTXD+	2	FTXD-
	3	FRXIN+	4	NC
	5	NC	6	FRXIN-
	7	NC	8	NC

GIGA Ethernet (Optional)

	Pin #	Signal Name	Pin #	Signal Name
	1	FTXD+	2	FTXD-
	3	FRXIN+	4	NC
	5	NC	6	FRXIN-
	7	NC	8	NC

Audio Line-Out

	Pin #	Signal Name
	1	GND
	2	LOUTL
	3	Open Touch
	4	Open Touch
5	VREFOUT	

2.6 Watchdog Timer

There are two watchdog timers in PPC-090T, we also provide DOS, Linux and WinCE example for your reference.

For more technical support, please visit: <http://tech.icop.com.tw> or download the PDF file at: dmp.com.tw/tech

Ch. 3

Hardware Installation

PPC-090T supports various kinds of storages for industrial application, divided into SATA Slim, CompactFlash or SD card (optional).

[3.1 Installing the SATA Slim](#)

[3.2 Installing the Compact Flash](#)

3.1 Installing the SATA Slim

[SPEC]

JEDEC SFF-8156 standard form factor

53 x 32 x 4.0 mm

SDM-SLIM-4G-V


SDM-SLIM-8G-V

SDM-SLIM-16G-V




[STEP]

1. Remove the nine screws in a diagonal pattern as the image below.



2. Place the SATA slim horizontally aligned and gently put into the socket until you feel a click.




3. Insert all nine screws into the screw holes.

3.2 Installing the Compact Flash

[STEP]

1. Remove the nine screws in a diagonal pattern as the image below.



2. Gently insert the CF card along the track. Caution: Please watch out for the direction which the CF card has to be face up.



3. Insert all nine screws into the screw holes.

Ch. 4

Driver Installation

[4.1 PPC-090T Development Note](#)

[4.2 BIOS Default Setting](#)

[4.3 Serial Ports Setting \(RS232/422/485\)](#)

VGA

The Vortex86DX2 processor is integrated RDC Display chip which is an ultra-low powered graphics chipset with total power consumption at around 1-1.5 W.

LAN

The Vortex86DX2 processor is integrated 10/100Mbps Ethernet controller that supports both 10/100BASE-T and allows direct connection to your 10/100Mbps Ethernet based Local Area Network for full interaction with local servers, wide area networks such as the Internet.

I/O and IRQ settings can be done by software with the supplied utility software, or it can be set for Plug and Play compatibility. The controller supports: Half / Full-Duplex Ethernet function to double channel bandwidth, auto media detection.

AUDIO

The ALC262 series are 4-Channel High Definition Audio Codecs with UAA (Universal Audio Architecture) featuring two 24-bit stereo DACs and three 20-bit stereo ADCs, they are designed for high performance multimedia desktop and laptop systems. The ALC262 series incorporates proprietary converter technology to achieve over 100dB Signal-to-Noise ratio playback quality; easily meeting PC2001 requirements and also bringing PC sound quality closer to consumer electronic devices.

OPERATING SYSTEM SUPPORT

The PPC-090T provides the VGA and LAN drivers for Linux, Windows CE, Windows XP Professional, and Windows Embedded standard (XPE).
(Linux can use with Compact Flash card only.)

Please get the drivers from ICOP technical support URL: tech.icop.com.tw

PPC-090T also supports most of the popular Linux distributions, for more detail information, please visit DMP official website: vortex86dx2

4.1 PPC-090T Development Note

< WINDOWS DEVELOPMENT GUIDE >

Windows Embedded CE 6.0 BSP, Windows Embedded Compact 7 BSP, and Windows Embedded Standard 2009 trial image with development notes, please visit technical website to get more information at <http://tech.icop.com.tw/>.

< LINUX INSTALLATION NOTE>

Please visit Linux technical website to get more information at ftp://ftp.dmp.com.tw/Linux_DEMO/Vortex86_Linux_Support_List_revised.htm.

4.2 BIOS Default Setting

If the system cannot be booted after BIOS changes are made, please follow below procedures in order to restore the CMOS as the default setting.



Press < **End** > Key, when the power on



Press < **Del** > to enter the AMI BIOS setup




Press < **F9** > to Load Optimized defaults




Press < **F10** > to Save configuration changes and exit setup

[Step 3] Choose the port you would like to change. For example, choose TXDEN1 for COM1 and press <Enter>. You will then see three options; select the desired type and press <Enter> to finish the setting.



The Serial Ports setting is finished.



Warranty

This product is warranted to be in good working order for a period of one year from the date of purchase. Should this product fail to be in good working order at any time during this period, we will, at our option, replace or repair it at no additional charge except as set forth in the following terms. This warranty does not apply to products damaged by misuse, modifications, accident or disaster. Vendor assumes no liability for any damages, lost profits, lost savings or any other incidental or consequential damage resulting from the use, misuse of, originality to use this product. Vendor will not be liable for any claim made by any other related party. Return authorization must be obtained from the vendor before returned merchandise will be accepted. Authorization can be obtained by calling or faxing the vendor and requesting a Return Merchandise Authorization (RMA) number. Returned goods should always be accompanied by a clear problem description.

All Trademarks appearing in this manuscript are registered trademark of their respective owners. All Specifications are subject to change without notice.