

MM74HC08 Quad 2-Input AND Gate

General Description

These AND gates utilize advanced silicon-gate CMOS technology to achieve operating speeds similar to LS-TTL gates with the low power consumption of standard CMOS integrated circuits. The HC08 has buffered outputs, providing high noise immunity and the ability to drive 10 LS-TTL loads. The 74HC logic family is functionally as well as pin-out compatible with the standard 54LS/74LS logic family. All inputs are protected from damage due to static discharge by internal diode clamps to $V_{\rm CC}$ and ground.

Features


- Typical propagation delay: 7 ns (t_{PHL}), 12 ns (t_{PLH})
- Fanout of 10 LS-TTL loads
- Quiescent power consumption: 2 µA maximum at room temperature
- Low input current: 1 µA maximum

Ordering Code

Commercial	Package Number	Package Description
MM74HC08N	N14A	14-Lead Molded Dual-In-Line (0.300" Wide)
MM74HC08M (Note 1)	M14A	14-Lead Molded Small Outline (0.150" Wide), JEDEC
MM74HC08MTC (Note 1)	MTC14	14-Lead Molded Thin Shrink Small Outline Package, JEDEC
MM74HC08SJ (Note 1)	M14D	14-Lead Molded Small Outline, EIAJ

Note 1: Devices also available in 13" Tape and Reel, Use suffix MX, SJX, and MTCX

Connection Diagram



Clamp Diode Current (I_{IK}, I_{OK})

DC Output Current, per pin (I_{OUT})

±20 mA

DC Output Current, per pin (I_{OUT})

±25 mA

DC V_{CC} or GND Current, per pin

 (I_{CC}) ±50 mA Storage Temperature Range (T_{STG}) -65° C to +150 $^{\circ}$ C Power Dissipation (P_{D})

(Note 4) S.O. Package only

Lead Temp. (T_L)

(Soldering 10 seconds)

Operating Conditions

	Min	Max	Units
Supply Voltage (V _{CC})	2	6	V
DC Input or Output Voltage	0	V_{CC}	V
(V_{IN}, V_{OUT})			
Operating Temp. Range (T _A)	-40	+85	°C
Input Rise or Fall Times			
(t_r, t_f) V_{CC} =2.0V		1000	ns
V _{CC} =4.5V		500	ns
V_{CC} =6.0V		400	ns

260°C

DC Electrical Characteristics (Note 5)

Symbol	Parameter	Conditions	V _{cc}	T _A =25°C		T _A =-40 to 85°C	T _A =-40 to 125°C	Units
				Тур		Guaranteed L	imits	
V _{IH}	Minimum High		2.0V		1.5	1.5	1.5	V
	Level Input Voltage		4.5V		3.15	3.15	3.15	V
			6.0V		4.2	4.2	4.2	V
V_{IL}	Maximum Low		2.0V		0.5	0.5	0.5	V
	Level Input Voltage		4.5V		1.35	1.35	1.35	V
	(Note 6)		6.0V		1.8	1.8	1.8	V
V _{OH}	Minimum High	V _{IN} =V _{IH}						
	Level Output	I _{OUT} ≤20 μA	2.0V	2.0	1.9	1.9	1.9	V
	Voltage		4.5V	4.5	4.4	4.4	4.4	V
			6.0V	6.0	5.9	5.9	5.9	V
		V _{IN} =V _{IH}						
		I _{OUT} ≤4.0 mA	4.5V	4.2	3.98	3.84	3.7	V
	I _{OUT} ≤5.2 mA	6.0V	5.7	5.48	5.34	5.2	V	
V _{OL}	Maximum Low	V _{IN} =V _{IH} or V _{IL}						
Level Output Voltage	I _{OUT} ≤20 μA	2.0V	0	0.1	0.1	0.1	V	
	Voltage		4.5V	0	0.1	0.1	0.1	V
			6.0V	0	0.1	0.1	0.1	V
		V _{IN} =V _{IH} or V _{IL}						
		I _{OUT} ≤4.0 mA	4.5V	0.2	0.26	0.33	0.4	V
		I _{OUT} ≤5.2 mA	6.0V	0.2	0.26	0.33	0.4	V
I _{IN}	Maximum Input Current	V _{IN} =V _{CC} or GND	6.0V		±0.1	±1.0	±1.0	μА
I _{cc}	Maximum Quiescent Supply Current	V _{IN} =V _{CC} or GND I _{OUT} =0 μA	6.0V		2.0	20	40	μА

600 mW

500 mW

Note 2: Absolute Maximum Ratings are those values beyond which damage to the device may occur.

Note 3: Unless otherwise specified all voltages are referenced to ground.

 $[\]textbf{Note 4:} \ \ \text{Power Dissipation temperature derating} -- \ \text{plastic "N" package: -12 mW/°C from 65°C to 85°C}.$

Note 5: For a power supply of 5V \pm 10% the worst case output voltages (V_{OH}, and V_{OL}) occur for HC at 4.5V. Thus the 4.5V values should be used when designing with this supply. Worst case V_{IH} and V_{IL} occur at V_{CC}=5.5V and 4.5V respectively. (The V_{IH} value at 5.5V is 3.85V.) The worst case leakage current (I_{IN}, I_{CC}, and I_{OZ}) occur for CMOS at the higher voltage and so the 6.0V values should be used.

Note 6: V_{IL} limits are currently tested at 20% of V_{CC} . The above V_{IL} specification (30% of V_{CC}) will be implemented no later than Q1, CY'89.

AC Electrical Characteristics

 V_{CC} =5V, T_A =25°C, C_L =15 pF, t_r = t_f =6 ns

Symbol	Parameter	Conditions	Тур	Guaranteed Limit	Units
t _{PHL}	Maximum Propagation		12	20	ns
	Delay, Output High to Low				
t _{PLH}	Maximum Propagation		7	15	ns
	Delay, Output Low to High				


AC Electrical Characteristics

 $\rm V_{CC}{=}2.0V$ to 6.0V, $\rm C_{L}{=}50$ pF, $\rm t_r{=}t_f{=}6$ ns (unless otherwise specified)


Symbol	Parameter	Conditions	V _{cc}	T _A =25°C		T _A =-40 to 125°C	Units	
				Тур	Guar	anteed Limits	7	
t _{PHL}	Maximum Propagation		2.0V	77	121	175	ns	
	Delay, Output High to Low		4.5V	15	24	35	ns	
			6.0V	13	20	30	ns	
t _{PLH}	Maximum Propagation		2.0V	30	90	134	ns	
	Delay, Output Low to High		4.5V	10	18	27	ns	
			6.0V	8	15	23	ns	
t _{TLH} , t _{THL}	Maximum Output Rise and		2.0V	30	75	110	ns	
	Fall Time		4.5V	8	15	22	ns	
			6.0V	7	13	19	ns	
C _{PD}	Power Dissipation Capacitance (Note 7)	(per gate)		38			pF	
C _{IN}	Maximum Input Capacitance			4	10	10	pF	


Note 7: C_{PD} determines the no load dynamic power consumption, $P_D = C_{PD} \ V_{CC}^2 \ f + I_{CC} \ V_{CC}$, and the no load dynamic current consumption, $I_S = C_{PD} \ V_{CC} \ f + I_{CC}$.

Physical Dimensions inches (millimeters) unless otherwise noted




14-Lead Molded Thin Shrink Small Outline Package, JEDEC Order Number MM74HC08MTC Package MTC14





14-Lead Molded Small Outline (0.150" Wide) JEDEC Order Number MM74HC08M Package M14A



LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DE-VICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMI-CONDUCTOR CORPORATION. As used herein:

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
- 2. A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

Fairchild Semiconductor Corporation Americas

Customer Response Center

Tel: 1-888-522-5372

www.fairchildsemi.com

Fairchild Semiconductor

Europe Fax: +49 (0) 1 80-530 85 86

Fax: +49 (0) 1 80-530 85 86

Email: europe.support@nsc.com

Deutsch Tel: +49 (0) 8 141-35-0

English Tel: +44 (0) 1 793-85-68-56

Italy Tel: +39 (0) 2 57 5631

Fairchild Semiconductor Hong Kong Ltd. 13th Floor, Straight Block, Ocean Centre, 5 Canton Rd. Tsimshatsui, Kowloon

Hong Kong Tel: +852 2737-7200 Fax: +852 2314-0061

National Semiconductor Japan Ltd. Tel: 81-3-5620-6175 Fax: 81-3-5620-6179